

LIMITED WARRANTY

HARDWARE: 3Com Limited ("3Com") warrants its hardware products to be free from defects in workmanship and materials, under normal use and service, for the following lengths of time from the date of purchase from 3Com or its Authorized Reseller:

Internetworking products	One year
Ethernet Stackable Hubs and Unmanaged Ethernet Fixed Port Repeaters	Lifetime*
	(One Year if not registered)
*Power supply and fans in these stackable hubs and unmanaged repeaters	One Year
Other hardware products	One year
Spare parts and spares kits	90 days

If a product does not operate as warranted during the applicable warranty period, 3Com shall, at its option and expense, repair the defective product or part, deliver to Customer an equivalent product or part to replace the defective item, or refund to Customer the purchase price paid for the defective product. All products that are replaced will become the property of 3Com. Replacement products may be new or reconditioned. Any replaced or repaired product or part has a ninety (90) day warranty or the remainder of the initial warranty period, whichever is longer.

3Com shall not be responsible for any software, firmware, information, or memory data of Customer contained in, stored on, or integrated with any products returned to 3Com pursuant to any warranty.

SOFTWARE: 3Com warrants that the software programs licensed from it will perform in substantial conformance to the program specifications therefor for a period of ninety (90) days from the date of purchase from 3Com or its Authorized Reseller. 3Com warrants the magnetic media containing software against failure during the warranty period. No updates are provided. 3Com's sole obligation hereunder shall be (at 3Com's discretion) to refund the purchase price paid by Customer for any defective software products, or to replace any defective media with software which substantially conforms to 3Com's applicable published specifications. Customer assumes responsibility for the selection of the appropriate applications program and associated reference materials. 3Com makes no warranty that its software products will work in combination with any hardware or applications software products provided by third parties, that the operation of the software products will be uninterrupted or error free, or that all defects in the software products will be corrected. For any third party products listed in the 3Com software product documentation or specifications as being compatible, 3Com will make reasonable efforts to provide compatibility, except where the non-compatibility is caused by a "bug" or defect in the third party's product.

STANDARD WARRANTY SERVICE: Standard warranty service for hardware products may be obtained by delivering the defective product, accompanied by a copy of the dated proof of purchase, to 3Com's Service Center or to an Authorized 3Com Service Center during the applicable warranty period. Standard warranty service for software products may be obtained by telephoning 3Com's Service Center or an Authorized 3Com Service Center, within the warranty period. Products returned to 3Com's Service Center must be pre-authorized by 3Com with a Return Material Authorization (RMA) number marked on the outside of the package, and sent prepaid, insured, and packaged appropriately for safe shipment. The repaired or replaced item will be shipped to Customer, at 3Com's expense, not later than thirty (30) days after receipt by 3Com.

WARRANTIES EXCLUSIVE: IF A 3COM PRODUCT DOES NOT OPERATE AS WARRANTED ABOVE, CUSTOMER'S SOLE REMEDY SHALL BE REPAIR, REPLACEMENT, OR REFUND OF THE PURCHASE PRICE PAID, AT 3COM'S OPTION. THE FOREGOING WARRANTIES AND REMEDIES ARE EXCLUSIVE AND ARE IN LIEU OF ALL OTHER WARRANTIES OR CONDITIONS, EXPRESS OR IMPLIED, EITHER IN FACT OR BY OPERATION OF LAW, STATUTORY OR OTHERWISE, INCLUDING WARRANTIES OR CONDITIONS OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. 3COM NEITHER ASSUMES NOR AUTHORIZES ANY OTHER PERSON TO ASSUME FOR IT ANY OTHER LIABILITY IN CONNECTION WITH THE SALE, INSTALLATION, MAINTENANCE OR USE OF ITS PRODUCTS.

3COM SHALL NOT BE LIABLE UNDER THIS WARRANTY IF ITS TESTING AND EXAMINATION DISCLOSE THAT THE ALLEGED DEFECT IN THE PRODUCT DOES NOT EXIST OR WAS CAUSED BY CUSTOMER'S OR ANY THIRD PERSON'S MISUSE, NEGLIGENCE, IMPROPER INSTALLATION OR TESTING, UNAUTHORIZED ATTEMPTS TO REPAIR, OR ANY OTHER CAUSE BEYOND THE RANGE OF THE INTENDED USE, OR BY ACCIDENT, FIRE, LIGHTNING, OR OTHER HAZARD.

LIMITATION OF LIABILITY. IN NO EVENT, WHETHER BASED IN CONTRACT OR TORT (INCLUDING NEGLIGENCE) SHALL 3COM BE LIABLE FOR INCIDENTAL, CONSEQUENTIAL, INDIRECT, SPECIAL, OR PUNITIVE DAMAGES OF ANY KIND, OR FOR LOSS OF REVENUE, LOSS OF BUSINESS, OR OTHER FINANCIAL LOSS ARISING OUT OF OR IN CONNECTION WITH THE SALE, INSTALLATION, MAINTENANCE, USE, PERFORMANCE, FAILURE, OR INTERRUPTION OF ITS PRODUCTS, EVEN IF 3COM OR ITS AUTHORIZED RESELLER HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. NOTHING HEREIN SHALL HAVE THE EFFECT OF LIMITING OR EXCLUDING 3COM'S LIABILITY FOR DEATH OR PERSONAL INJURY CAUSED BY NEGLIGENCE.

Some states do not allow the exclusion of implied warranties or the limitation of incidental or consequential damages for consumer products, so the above limitations and exclusions may not apply to you. This warranty gives you specific legal rights which may vary from state to state. Nothing in this warranty shall be taken to affect your statutory rights.

GOVERNING LAW: This Limited Warranty shall be governed by the laws of England.

3Com Limited, ISOLAN House, Brindley Way, London Road, Hemel Hempstead, Hertfordshire, HP3 9XJ, UK. 44(0)442 278000

23/12/93

LinkBuilder

How To Install And Use The TP Transceiver Interface Module

3C12063




Figure 1

This manual details the installation and use of the 3Com TP Transceiver Interface Module, 3C12063. Please retain this manual with your other 3Com manuals for future use.

1 Interworking Information

The 3Com[®] LinkBuilder[®] TP Transceiver Interface Module has been designed to the IEEE 802.3 10BaseT specification.

The Transceiver Module can transmit and receive Ethernet 10 Mbit/sec traffic over Shielded or Unshielded Twisted Pair cable. The Transceiver Module features crossover (MDI/MDIX) switching, SQE Test selection and link monitoring using the Link LED (Light Emitting Diode).

The Transceiver Module is used to provide connectivity to twisted pair cable on the following LinkBuilder products:

- ECS modules (3C12076, and 3C12050/1)
- MSH modules (3C18110, 3C18120, 3C18124, 3C18146 and 3C18600)
- FMS Stackable Hubs (3C16250, 3C16265, 3C16271 and 3C16371)
- FMS II Stackable Hubs (3C16665, 3C16670, 3C16671 and 3C16672)

LinkBuilder TP/12 (3C16170) and LinkBuilder TP/8i (3C16181) hubs Repeaters (3C16170, 3C16200, 3C16210 and 3C16505).

This product has the benefit of a "lifetime warranty", details of which are given on page 4 of this manual.

2 Setting up the Module

MDI/MDIX

The PL2 component switches the TP port between MDI and MDIX.

MDI is the default setting and allows the Transceiver Module to be connected by normal twisted pair cable to an MDIX port on another hub to form an inter-repeater link.

If MDIX is selected the Transceiver Module can be connected to a workstation or any other Data Terminal Equipment. It can also be connected to another hub which is already set to MDI to form an inter-repeater link.

See Figure 1 to locate the MDI/MDIX jumper and then Figure 2 to ensure you have the correct selection.



Figure 2

SQE Test

The PL1 component allows you to enable or disable the SQE Test. The SQE Test is used by 802.3 transceivers to confirm that the transceiver is functioning correctly. The function *must* be disabled for operation when installed in a Repeater. The function should be enabled for operation when connected to a LinkBuilder ECS Local Bridge Module 3C12050/1.

The Transceiver Module is supplied with SQE Test disabled.

See Figure 1 to locate the SQE Test jumper and then Figure 3 to ensure you have the correct selection.



Figure 3

3 Installation



Only qualified personnel should install this device. Observe normal anti-static precautions! Use an earthed wrist-band!

A 16-pin header and a 16-way edge connector are mounted on the Transceiver Module for connection to a Module, Stackable Hub or Repeater.

A Twisted Pair cable can be connected to the RJ45 connector on the front of the Transceiver Module.

Remove the blanking plate from the unit in which you are going to install the Transceiver Module. The relevant manual will tell you where to find the plate.

Keep the blanking plate in a safe place so that it can be replaced if the Transceiver Module is removed.

Installing in a Stackable Hub or Repeater

For FMS Stackables and Repeaters, hold the mounting panel with the pin header side of the board down. See Figure 1 to locate the pin header.

For FMS II Stackables, hold the mounting panel with the pin header side of the board up.

Insert the edge connector end of the Transceiver Module into the rear of the mother device.

Slide the Transceiver Module in carefully to engage in the slot and push it fully home.

Fix the mounting panel of the Transceiver Module to the back panel using the two screws from the blanking plate.

Installing in an ECS or MSH Module

Before you install the Transceiver Module, you must remove the mother device from the network and all power sources. Modules must be removed from the Chassis (you do not need to power down the chassis first). The 3C18146 Expansion Module must be separated from its mother module. See the relevant 'How to Install and Use...' manual.

Position the Module on a flat surface with the 16-way socket facing up. Hold the Transceiver Module by the mounting panel and board edge with the header pins facing down. See Figure 1 to locate the header pins. Pass the board of the Transceiver Module through the cut-out in the front panel. Align the socket on the Module with the pins on the Transceiver Module and push down firmly to connect.

With the 3C18146 Expansion Module, you align the header and pins and press gently to engage the pins. Turn the pair over to rest on the Transceiver Module and press firmly close to the header to complete connection.

Fix the mounting panel of the Transceiver Module to the module using the two screws from the blanking plate.

Connection

Before proceeding with the installation of the module, check that the host equipment is set up to take the module. See the relevant 'How to Install and Use...' manual.

Re-install the mother device into its chassis and/or network.

Connect the Transceiver Module to the TP segment.

4 Operation

Link LED

The Link LED on the front of the Transceiver Module lights green when a link is detected. If a link is not present the LED does not light.

5 Problems

If the Link LED does not light when the Transceiver Module is installed the cause may be one of the following:

Both ends of the link are configured as MDI - change one to MDIX.

Both ends of the link are configured as MDIX - change one to MDI.

The far end device is not powered up or may be faulty. Check the device.

The cable linking the devices is broken or incorrectly wired. Change the cable.

Disclaimer

Information in this document is subject to change without notice and does not represent a commitment on the part of 3Com. 3Com reserves the right to revise or change this document without obligation of 3Com to notify any person of the revisions or changes. Information contained in this document is believed to be accurate at the time of publication but no liability whatsoever can be accepted by 3Com arising out of any use of this information.

Standards

The 3Com RJ45 Transceiver Module 3C12063 has been designed to comply with the following standards:

Functional:	PLS & AUI Specification ISO 8802.3 Sect. 7 & 10
Safety:	UL 1950, EN 60950, CSA 22.2 #950
E.M.C.	FCC Part 15 (Level A) EN55022 (Level A) VFG 243 (Level B) IEC 801 (Parts 2-6)
Environment	IEC68 Operating Temperature: 0 to 50°C 32 to 122 °F Humidity - 10 to 90% Non Cond.

Radio Frequency Interference Statement

This equipment has been tested with a class A computing device and has been found to comply with part 15 of FCC Rules. Operation in a residential area may cause unacceptable interference to radio and TV receptions requiring the operator to take whatever steps are necessary to correct the interference.

This digital apparatus does not exceed the Class A limits for radio noise emissions from digital apparatus as set out in the interference-causing equipment standard entitled "Digital Apparatus", ICES-003 of the Department of Communications.

Cet appareil numérique respecte les limites de bruits radioélectriques applicables aux appareils numériques de Classe A prescrites dans la norme sur le matériel brouilleur : "Appareils Numériques", NMB-003 édictée par le ministre des Communications.

3Com and LinkBuilder are registered trademarks of the 3Com Corporation.

Document No: DUA1206-3AAA01
Revision : 00

Issued: November 1994

© 1994 3Com Technologies Limited

